



All outdoor Antennafiers™ are powered via a DC Feed. These devices inject DC power onto the center of the coaxial cable. In addition they have a diagnostic feature which is displayed via three LED's that yield amplifier status such as RX, PWR, TX, or Fault.

These DC Feeds are rated for indoor use on any of our outdoor Amplifier Products.

Featured Highlights:

- LED Status Indications
- Low RF Loss: 900MHz ≤ 0.3dB
 2.4GHz ≤ 0.3dB
 5GHz ≤ 1.0dB
- Internal Transient Voltage Protection
- Rugged Housing with mounting plate

LED Status:

Mode	TX	RX
Transmit	Red	-
Receive	-	Green
Fault	-	-

Mechanical:

DC Connector	2.1mm I.D. (+), 5.5MM O.D. (-)
Mechanical Size	4.75" x 2.0" x 1.1" including mounting bracket
Weight	7 oz

Ordering Guide:

Model	Frequency Band
DCF-915L DCF-915UD	902-928MHz
DCF-2400S DCF-2400L DCF-2400LG DCF-2400P	2.4-2.485GHz
DCF-5800S	4.9-5.8GHz

9017 Cincinnati Columbus Rd.
West Chester, Ohio 45069
PH: 513/777-2774